

### *Mounting hardware*

We've included all the needed hardware to mount the power supply on top or underneath a Pedaltrain or Temple Audio pedalboard. You can of course also attach it to boards of other brands. Look on CIOKS web site for more information and mounting guides.

### **Not included accessories**

#### *Mains Link Adapter or Mains link cable*

This adapter or cable type allows you to link two or more of the link power supplies together and power several units using one single mains power cord.

#### *More Flex cables*

To power one pedal using one outlet you simply use a single suitable standard Flex cable and that's it. In case the plug type or length you need is not included with your unit there's a big selection of standard Flex cables to choose from and to be ordered separately. In case of an odd voltage or current requirement you might need one of the Special Flex cables available. Please read more about these and how to use them on CIOKS web site. They really open up for even more versatility and flexibility in terms of what you can power with your unit.

### **Powering different pedal types**

This issue is different for every individual rig, therefore please e-mail your specific questions regarding powering your pedals using CIOKS power supplies directly to [support@cioks.com](mailto:support@cioks.com).

### **Technical specifications**

AC mains input: 110-120VAC 60Hz or 220-240VAC 50Hz, max. 15W

Outputs: Outlet 1-2: 9V DC / 250mA each, isolated  
Outlet 3-4: 9 or 12V DC / 100mA each, isolated

Size: 115x88x31mm (excl. rubber feet)

Weight: 0,8kg

Warranty period: 5 years worldwide

### **What's in the box?**

- CIOKS Adam power supply
- mains power cord
- 6 Flex cables
- pedalboard mounting hardware (2 screws and a hex key)
- manual
- product sheet (drill template)
- Flex guide

# **CIOKS Adam link**

## **Power Supply for Effect Pedals**

### **User's Manual**

reversion 1.1 – March 2017

### **Introduction**

Since 1991 the Danish company CIOKS has been providing guitar and bass players with reliable power supplies dedicated for effect pedals. After our very first product CIOKS Baby power supply was out in 1991, the Big John and Double Jack were launched in year 1995. Three more units were introduced in 2007 forming our Standard range of dedicated power supplies for effect pedals.

To follow our slogan "More power, more features, more design", we have in 2013 launched CIOKS link range. Three of the Standard range products have been dramatically upgraded and went through a spectacular face-lift, where the only thing left are their original names. CIOKS Schizophrenic link, Big John link and AC Rider link were our new babies in year 2013. Small size, yet very powerful and each model with an individual character and force. The unique mains link feature allows you to merge two or more power supplies giving you the possibility to create a power supply bank matching your individual needs. Just one single mains power cord will power two or three power supplies, where you always have a courtesy AC mains outlet available on the last unit. You can of course also use them as standalone power supplies, getting just one to start with and extend with time.

In year 2014 we've launched our smallest wonder – Adam link power supply. A perfect match for the smallest pedal boards like the Pedaltrain models nano, mini or metro. Super flat design and small but still powerful enough to power any two Strymon pedals or other medium current ones of the two 250mA outlets. The remaining two will at lower currents provide 9 or 12V or even 18 or 24V using series adapter Flex. Adam link is also a nice four isolated outlets add-on to any other CIOKS link power supply.

### **Features**

- 4 isolated outlets with a total output current of 700mA
- two outlets configurable to either 9 or 12V
- short circuit protection of all outlets
- advanced LED monitoring of each outlet
- 120 or 230V mains voltage operation
- detachable mains power cord
- CIOKS unique mains link feature
- 6 Flex cables included
- very easy mounting with pedalboards, all needed hardware included
- compatible with Pedaltrain and Temple Audio pedalboards

## Overview

### Right side

On the right side of the enclosure you'll find the 4 outlets of the power supply as RCA sockets which all are centre positive. Correct polarity for the pedal is achieved by using the right Flex cable.

The red settings switch with two white knobs placed just to the right of the outlets should be used to set the output voltage of outlets 3 and 4. The left knob is for setting of outlet 3, the right one is for outlet 4.

Knob no. *	Function	Knob down	Knob up
1	Outlet 3	9V DC	12V DC
2	Outlet 4	9V DC	12V DC

\* counting from left, opposite order of the white digits on the red switch (if you can see them)

### Top

CIOKS logo has a red LED placed in the middle of the letter 'O'. When this LED is lit the power supply is connected to mains and operates.

On top of the enclosure you see the output voltage and max. current rating of each outlet printed just above the outlet sockets. The top figure is the voltage and the DC in the middle line tells you it's a direct current outlet. Outlets with two possible voltage settings have both values stated as 9/12. The bottom figures states the maximum current capability of each outlet in mA.

The status of each isolated output is shown by a LED indicator also situated on top of the enclosure just above the voltage figure. The function of this advanced and unique monitoring feature is described in detail later on.

### Left side

On the left side of the enclosure you'll find the AC power input connector, which is a C6 type according to the IEC 60320 standard also used in many laptop adapters. On the same side as the AC mains input you'll find the mains voltage selector switch and the fuse.

Mains voltage selector switch should be used for setting the correct mains voltage 115 or 230V. The Japanese version is made only for a 100V nominal mains voltage and has no mains voltage selector switch.

The fuse is the only part which may be replaced by the user. In case it's blown, replace with a 5x20mm, T 200mA (slow blow/time lag) type.

### Bottom

The four detachable rubber feet are situated on the bottom of the enclosure. On this same surface you'll find 4 holes with metric M4 threads, which should be used for easy mounting of

the power supply to a pedalboard. Do not use screws, which would go further than 5mm inside the unit. Have a look at the mounting guide on CIOKS web site.

## Getting started

First make sure that the voltage value chosen on the voltage selector switch matches the mains voltage in your wall socket. Connect the mains power cord to the power supply and mains. Using the right Flex cable types connect your pedals to the outlets of power supply making sure that the voltage and current is correct for every pedal.

## Advanced LED Monitoring feature

Each isolated outlet has its individual LED status indicator. The indicator is fully lit in normal operation of a particular outlet. Its light gets dim when you operate just on the edge of the current limit. If you overload or short circuit an outlet, the respective LED indicator turns off.

The LED indicators of outlets 1, 2, 5 and 6 with selectable output voltages also show you the voltage set by the settings switch. In case a higher voltage than the default 9V setting is selected for a given outlet, its respective LED indicator will be lit with higher intensity than the other indicators.

All indicators take into account the actual level of mains voltage when monitoring a possible overload. The current limits for each outlet or section of the power supply are specified at nominal level of the mains voltage. In Europe it's 230V, 120V in e.g. United States and 100V in Japan. If the mains voltage is higher than nominal, you can draw more current from the power supply than stated in the specifications. This would never be a problem. A more common situation though, is when the mains voltage is lower than nominal. In such a case maximum current ratings for each outlet or section might be diminished.

The advanced LED monitoring of each isolated outlet will alert you in case of an overload or short circuit. If such a situation happens you know where to look to solve the problem. A glance at the LED status indicators and you have proof of 100% clean power to your pedals.

## Included accessories

### Flex cables

CIOKS offers a great selection of different Flex cable types for connection your pedals to the power supply. Below you see a list of the included Flex cables with your unit:

- Type 1 – black with 5,5/2,1mm centre negative DC-plug x4
- Type 5 – black with 3,5mm tip positive jack-plug x1
- Type 1 – Split Flex (to power two pedals of one outlet) x1